

Color IR Dome Cameras

JCC-MIR975D

1/3" Color Dome Camera



JCC-MIR975XD

1/3" Color ExView CCD Dome Camera



JCC-MIR978XD

1/3" High Res. Color ExView CCD Dome Camera



3-Axis Mechanism





Features

- Built-in Vari-Focal DC Drive Lens
- Built-in 24 pieces IR-LED
- Effective range up to 20 M
- JCC-MIR975D:
 - 1/3" Sony HAD CCD
 - NTSC:537x505 / PAL:537x597 Pixels
 - 380 TV Lines / 0 Lux with IR
- JCC-MIR975XD:
 - 1/3" Sony Exview CCD
 - NTSC:537x505 / PAL:537x597 Pixels
 - 380 TV Lines / 0 Lux with IR
- JCC-MIR978XD:
 - 1/3" Sony Exview HAD CCD
 - NTSC:811x508/PAL:795x596 Pixels
 - 470 TV Lines / 0 Lux with IR
- Auto White Balance
- Gain Control : High / Low
- DC 12 V
- 3.7~12.0 Varifovocal Lens
- IR Cut Filter Removable (ICR)

Specification

Model	JCC-MIR975D	JCC-MIR975XD	JCC-MIR978XD
Pick Up Element	1/3" Color Sony Super HAD	1/3" Color Sony Ex-View HAD	1/3" Color Sony Ex-View HAD (High Res.)
Picture Element	NTSC: 537(H) x 505(V) PAL: 537(H) x 597(V)		NTSC: 811(H) x 508(V) PAL: 795(H) x 596(V)
Horizontal Frequency	NTSC: 15.734 KHz ; PAL: 15.625 KHz		
Vertical Frequency	NTSC: 59.94 Hz ; PAL: 50 Hz		
Synchronization	Internal		
Scanning System	2 : 1 Interlace		
Flickless Mode	On/Off (NTSC:1/100, PAL:1/120)		
Resolution	Horizontal 380 TV Lines		Horizontal 470 TV Lines
Sensitivity	0.2 Lux @F2.0 (Day) 0 Lux (IR on)	0.5 Lux @F2.0 (Day) 0 Lux (IR on)	0.15 Lux @F2.0 (Day) 0 Lux (IR on)
S/N Ratio	More than 48 dB (AGC Off)		
White Balance	Automatic (2500 K ~ 9500 K)		
Gain Control	High / Low		
Electronic Shutter	NTSC:1/60~1/100,000; PAL:1/50~1/110,000		
Gamma Correction	0.45		
Lens Built-in	Vari-Focal 3.7~12mm (ICR) / F1.6~3.0		
Video Output	1.0 Vp-p Composite Video Output; 75 Ohms		
Infrared Luminary	24 pieces IR-LED		
Wavelength	850 nm		
Illuminating Distance	20 Meters		
Operating Temperature	- 10° ~ +50 °C / RH 85% or Less		
Power Supply	DC12V		
Power Consumption	IR On:425mA Max., IR Off:117mA Max.		IR On:400mA Max., IR Off:200mA Max.

Dimension



Optional



Wall-mount Bracket
(Optional)

■WMB-X12