

# PIR & Smoke Detector Hidden Cameras

**JBC-351PA**  
1/3" B/W PIR Camera



## Features

- 1/3" Sony Color CCD Sensor
- EIA: 537(H) x 505(V)  
CCIR: 537(H) x 597(V)  
420 TV Lines / 0.1 Lux@F2.0
- Auto Gain Control
- Auto Electronic Shutter
- 3.7mm / F2.0 Pinhole Cone Lens  
Built-in
- DC 12V
- With PIR Sensor & Audio Built-in

## Specification

Model	JBC-351PA
Image Sensor	1/3" Sony Super HAD CCD Sensor
Picture Element	EIA: 537(H) x 505(V) ; CCIR: 537(H) x 597(V)
Synchronization	Internal
Resolution	Horizontal 420 TV Lines
Low-light Sensitivity	0.1 Lux @F2.0
S/N Ratio	More than 48 dB (AGC OFF)
Electronic Shutter	Auto: 1/60 (50) sec. ~ 1/100,000 sec
White Balance	N/A
Gain Control	Auto Gain Control (AGC)
Lens Built-in	3.7mm/F2.0 Pinhole Cone Lens
Video Output	1.0 Vp-p Composite Video Output ; 75 Ohm
Power Supply	DC 12V
Power Consumption	Max. 1.7 W
Operating Temperature	- 10 ~ 50 °C ( 14 ~ 122 °F)
Audio Output	2V p-p 50Ω(RCA)
Built-in PIR Sensor	Yes
PIR NC/NO Relay Output	1 A /AC 125 V, 2A /DC 30 V
PIR Relay Alarm Time	2 ~ 40 sec. Adjustable
PIR Detection Angle	Hor. = 100 / Vert. = 45 degree
PIR Detection Range	Max. 10 Meters

## Dimension

